FXO 10GigE

fxo540MXGE



□□

□□	fxo540MXGE
□□ □□	F002090
□□ □□□	FXO 10GigE
□□	Available

□□

□□ □□	Area scan
□□□	Mono
□□□□	Visible
□□□□ □□	400 nm to 1000 nm
□□□	5,320 × 4,600 (24.50 MP)
□□ □□	Sony IMX540
□□ □□□□ (□□)	cmos
□□ □□	Global shutter (GS)
□□ □□	14.58 × 12.6 mm (19.27 mm, Type 1.2)
□□ □□	2.74 µm × 2.74 µm

□□ □□

□□ □□ □□	8-bit, 12-bit
□□□□ □□ □□	mono8, mono12

□□□ □□

□□□□ □□□	72 dB
SNR	39.11 dB

□□□ □ □□

□□ □□□ □□	30.4 fps
□□ □□	9 µs to 60 s
□□	0.0 dB to 48.0 dB

I/O □ □□

□□□ □□	0 x LVDS input, 0 x LVDS output, 0 x TTL input, 0 x TTL output, 2 x 24V input, 4 x Open drain output,
□□ □□□ □□	1 x RS232 input, 1 x RS232 output, 0 x RS422 input, 0 x RS422 output,
□□□ □□	1 x Optical isolated input, 0 x Optical isolated input,
I/O □□□	12-pin Hirose HR10A-10P-12S
□□ □□ □□	10 to 25VDC, Power over Ethernet
□□ □□	External: 10 W (typical)

□□ □□

□□ □□ (□□□)	-10 °C to 60 °C

□□□ □□

□□ □□ (L x W x H mm)	76 × 50 × 50
□□/□□ □□	K9 - AR coating - 400-850nm
IP □□	IP30
□□ □□□	C-Mount
□□	240 g

□□□ □□□ □ FPGA

□□□ □□ (RAM)	896 MByte
□□□□ □□□ (□□□)	32 MByte

□□□□□

□□□ □□□□□	10gige
□□□□□ □□□	(RJ-45)
□□ □□	GigE Vision 2.0

FW □□ - □□□ □□

□□ □□	manual, auto, external


FW □□ - □□□ □□

□□ □□	auto, manual
□□□ □□ □□	roi, lut, mirror-image, dpc, shading-correction, ffc


FW □□ - □□□ □□


□□□ □□/□□□	internal, software, external
□□□ □□ □□	PTP, User Sets, POE, PWM(4), Sequencer,


Quantum Efficiency





Technical Drawing


















I/O pin assignment

Hirose 12 Pin



1	VIN –	(GND)	7	OUT 1	(open drain)
2	VIN +	(10 V to 25 V DC)	8	OUT 2	(open drain)
3	IN 4	(RXD RS232)	9	IN 3 +	(opto In +)
4	OUT 4	(TXD RS232)	10	IN 3 –	(opto In –)
5	IN 1	(0 - 24V)	11	OUT 3	(open drain)
6	IN 2	(0 - 24V)	12	OUT 0	(open drain)