Allied Vision



# HR 10GigE

## hr51CXGE-G2

| □□ | |
|---|---|
| □□ | hr51CXGE-G2 |
| □□ □□ | F004154 |
| □□ □□□ | HR 10GigE |
| □□ | Deleted |

| □□ | |
|---|---|
| □□ □□ | Area scan |
| □□□ | Color |
| □□□□ | Visible |
| □□□□ □□ | 400 nm to 1000 nm |
| □□□ | 8,424 × 6,032 (51.00 MP) |
| □□ □□ | Gpixel GMAX4651-BVC-BU2 |
| □□ □□□□ (□□) | cmos |
| □□ □□ | Global shutter (GS) |
| □□ □□ | 38.75 × 27.75 mm (47.66 mm, 35mm Full Frame) |
| □□ □□ | 4.60 µm × 4.60 µm |

| □□ □□ | |
|---|---|
| □□ □□ □□ | 8-Bit,12-Bit |
| RGB □□ □□ | bayer8, bayer12 |

| □□□ □□ | |
|---|---|
| □□□□ □□□ | 65 dB |
| SNR | 42.6 dB |

## □□□ □ □□

| | |
|---|---|
| □□ □□□ □□ | 23.7 fps |
| □□ □□ | 60 µs (max) |
| □□ | 0.0 dB to 40.0 dB |

## I/O □ □□

| | |
|---|---|
| □□□ □□ | 0 x LVDS input, 0 x LVDS output0 x TTL input, 0 x TTL output, 2 x 24V input, 4 x Open drain output |
| □□ □□□ □□ | 1 x RS232 input, 1 x RS232 output, 0 x RS422 input, 0 x RS422 output |
| □□□ □□ | 1 x Optical isolated input, 0 x Optical isolated Input, |
| □□ □□ □□ | 10 to 25VDC |
| □□ □□ | External: 17 W (typical at 12 VDC) |

## □□□ □□

| | |
|---|---|
| □□ □□ (L x W x H mm) | 77 × 70 × 70 |
| □□/□□ □□ | IR-Cut 680 |
| IP □□ | IP30 |
| □□ □□□ | M58x0.75 |
| □□ | 380 g |

## □□□ □□□ □ FPGA

| | |
|---|---|
| □□□ □□ (RAM) | 448 MByte |

## □□□□□

| | |
|---|---|
| □□□ □□□□□□ | 10gige |
| □□□□□ □□□ | (RJ-45) |

## FW □□ - □□□ □□

| | |
|---|---|
| □□ □□ | Manual, Auto |
| □□ □□ | Auto, Manual |
| □□□ □□□ □□ | auto, manual |
| □□□ □□ □□ | FW Features - Image Control |


## FW □□ - □□□ □□

| | |
|---|---|
| □□□ □□/□□□ | INTERNAL,SOFTWARE,EXTERNAL |

## FW □□ - □□□ □□

| | |
|---|---|
| □□□ □□ □□ | User Sets, POE, PWM(4), Sequencer, |


## Quantum Efficiency




Allied Vision

## Technical Drawing


### front





### back





### cross section





### right side




top



bottom





3D



## I/O pin assignment

Hirose 12 Pin



| | | | | | |
|---|---|---|---|---|---|
| 1 | VIN – | (GND) | 7 | OUT 1 | (open drain) |
| 2 | VIN + | (10 V to 25 V DC) | 8 | OUT 2 | (open drain) |
| 3 | IN 4 | (RXD RS232) | 9 | IN 3 + | (opto In +) |
| 4 | OUT 4 | (TXD RS232) | 10 | IN 3 – | (opto In –) |
| 5 | IN 1 | (0 - 24V) | 11 | OUT 3 | (open drain) |
| 6 | IN 2 | (0 - 24V) | 12 | OUT 0 | (open drain) |